



## Testing & Inspection Intervals for Electrical Equipment

**Extract: AS/NZS 3760:2010**

**\*\*This extract must be read in accordance with Clause 2.1 with the entire AS/NZS Standard**

Type of environment and/or equipment (a)		Interval between Inspection & Tests				
		Equipment including Class I equipment, Class II equipment, cord sets, cord extension sets and EPODs (b)	Residual Current Device (RCDs)			
			Push-button test - by user		Operating time & push-button test	
			Portable (c)	Fixed (d)	Portable (e)	Fixed (f)
1	Factories, workshops, places of work or repair, manufacturing, assembly, maintenance or fabrication.	6 Months	Daily, or before every use, whichever is longer	6 Months	12 Months	12 Months
2	Environment where the equipment or supply flexible cord is subject to flexing in normal use OR is open to abuse OR is in a hostile environment.	12 Months	3 Months	6 Months	12 Months	12 Months
3	Environment where the equipment or supply cord is NOT subject to flexing in normal use and is NOT open to abuse and is NOT in a hostile environment.	5 Years	3 Months	6 Months	2 Years	5 Years
4	Residential type areas of: hotels, residential institutions, motels, boarding houses, halls, hostels accommodation houses, and the like	2 Years	6 Months	6 Months	2 Years	2 Years
5	Equipment used for commercial cleaning	6 Months	Daily, or before every use, whichever is the longer	N/A	6 Months	N/A
6	Hire Equipment Inspection	Prior to Hire	Including push-button test by hirer prior to hire		N/A	N/A
	Test & Tag	3 Months	N/A		3 Months	12 Months